

Product Datasheet - Technical Specifications



More information in our Web-Shop at **• www.meilhaus.com**

Your contact

Technical and commercial sales, price information, quotations, demo/test equipment, consulting:

Tel.: +49 - (0)81 41 - 52 71-0

E-Mail: sales@meilhaus.com

Meilhaus Electronic GmbH Am Sonnenlicht 2

 Am Sonnenlicht 2
 Tel. +49 - (0)81 41 - 52 71-0 E

 82239 Alling/Germany
 Mail sales@meilhaus.com

 Mentioned company and product names may be registered trademarks of the respective

Mentioned company and product names may be registered trademarks of the respective companies. Errors and omissions excepted. © Meilhaus Electronic.

www.meilhaus.com

IT-N2133

Parameter	•	IT-N2133	
	Voltage	0 - 150V	Voc 165V
Rated values	Current	0 - 10A	
	Power	0 - 1500W	1500W-220ac; 850W-110ac
	Resistance	/	
Line regulation	Voltage	≤0.01%+2mV	Sense mode
±(%of Output+Offset)	Current	≤0.01%+1mA	
Load regulation	Voltage	≤0.01%+3mV	Sense mode
±(%of Output+Offset)	Current	≤0.01%+1mA	
	Voltage	10mV	
	Current	1mA	
Setup resolution	Power	/	
	Resistance	/	
	Voltage	1mV	
Readback resolution	Current	1mA	
	Power	/	
	Voltage	≤0.03%+30mV	
	Current	≤0.05%+5mA	
Setup accuracy	Power	/	
	Resistance	/	
	Voltage	≤0.03%+20mV	
Readback accuracy	Current	≤0.05%+5mA	
	Power	/	
Ripple (20hz-20Mhz)	Voltage	≤300mVp-p/≤40mVrms	
	Voltage RMS	40mVrms	
Rippie (20nz-300Knz)	Current RMS	≤5mArms	20mAp-p
Setup	Voltage	≤0.003%+1.5mV	
Temp.coefficient			
(%of	Current	≤0.015%+0.35mA	
Output+Offset)/ C	Valtaga	<0.0020/ 1.1m)/	
Temp.coefficient	voitage	≤0.002%+1mV	
(%of Output+Offset)/℃	Current	≤0.012%+0.35mA	

Rise time(No-load)	Voltage	≤20ms	The voltage rise and fall time refers to the change of the set value, the set value is 1%-100% or 100%-1%
Rise time(Full-load)	Voltage	≤20ms	The current rise and fall time refers to the change of the set value, set value 1%- 100% or 100%-1%
Fall time(No-load)	Voltage	≤20ms	Current rise time \leq 30us 10%-90%
Fall time(Full-load)	Voltage	≤20ms	Current drop time \leq 30us 10%-90%
Transient response time	Voltage	300us	50%-100% load recovery to 100mV
	Voltage	220V/110V	
AC Input	Frequency	50/60Hz	
Setup stability -30min	Voltage	≤0.01%+1mV	
(%of Output +Offset)	Current	≤0.02%+1.5mA	
Setup stability -8h	Voltage	≤0.015%+1.2mV	
(%of Output +Offset)	Current	≤0.02%+2mA	
Readback stability -	Voltage	≤0.01%+1mV	
30min (%of Output +Offset)	Current	≤0.02%+1.5mA	
Readback stability -8h	Voltage	≤0.015%+1.2mV	
(%of Output +Offset)	Current	≤0.02%+2mA	
Efficiency		72% (Typical)	
Remote Sense Com	pensation	≤2V	
Command Resp	oonse	≤15ms	
Power Facto	or	≥0.98	
Maximum input o	current	11A	
Maximum inp apparent pov	out ver	2100VA	
Storage temper	ature	-10°C - 70°C	
Protective func	ction	OVP/OCP	
Communication Ir	nterface	LAN/USB	
Isolation (output to	ground)	1500Vdc	
Isolation (input to	ground)	1500Vac	
Working temper	ature	0 - 40°C	

Fuse Specifications	T15A	The fuse is inside the power supply
Number of parallel machines	Not Support	
Number of machines in series	No limit	The output terminal common mode voltage does not exceed 1500VDC
Protection class	IP20	
Safety Regulation	IEC 61010	
Cooling Style	Fans	
Dimension (Removal handle, etc., assembly dimensions)	450 mm (D) x 214 mm (W)) x 88.2 mm(H)
Dimension(Overall)	529.5 mm (D) x 255 mm	(W) x 108.2 mm(H)
Weight (net weight)	9kg	

	Parameter		Remark
	Voltage input range of IO ports	0~5V	
	IO input pin source and sink IMAX	47mA	
	Voltage output range of IO ports	0~5V	
Ю	IO output pin source and sink IMAX	0.45mA	
	IO port response time	10ms	Minimum action time, from given signal to trigger action
	IO port to output DC	<15V	The damage is short circuit, the maximum current is 1A
	LIST bandwidth	-	
	Voltage/Current Step Resolution	1mV 1mA	
LIST	Signal rise and fall time range	1mS~3600S	The actual effect refers to the rise/fall time of the specification, here is the range of setting items
	Maximum number of steps	100	
	Maximum number of files	20	
	Number of GROUP	-	No group function
	Time accuracy	≤10ms/Step	
METER	Sampling Rate	1kHz±1%	

Storage depth

* This information is subject to change without notice.