

Product Datasheet - Technical Specifications



More information in our Web-Shop at ► www.meilhaus.com

Your contact

Technical and commercial sales, price information,
quotations, demo/test equipment, consulting:

Tel.: **+49 - (0)81 41 - 52 71-0**

FAX: **+49 - (0)81 41 - 52 71-129**

E-Mail: sales@meilhaus.com

Meilhaus Electronic GmbH
Am Sonnenlicht 2
82239 Alling/Germany

Tel. **+49 - (0)81 41 - 52 71-0**
Fax **+49 - (0)81 41 - 52 71-129**
E-Mail sales@meilhaus.com

Mentioned company and product names may be registered trademarks of the respective companies. Errors and omissions excepted. © Meilhaus Electronic.

LPA10 / TPA10

Active Probe Adapter

Data Sheet
DS60APA_E01A



LPA10

TPA10

Product Overview

SIGLENT's LPA10 / TPA10 are active probe adapters for using non-SIGLENT active probes on SIGLENT's oscilloscopes with the SAPBus interface.

The LPA10 is for adapting probes with LeCroy Probus interface and the TPA10 is for probes with Tektronix TekProbe interface level II.

The adapters provide all necessary power and offset control to the attached probes. No extra power supply is needed.

Probes with LeCroy Probus interface can be automatically detected by using the LPA10 and proper oscilloscope firmware. Once the probe is attached, the probe attenuation is automatically set by the oscilloscope.



LPA10 Specifications

Oscilloscope Supported Probes	SDS5000X
AP033	0.9.1B2 firmware and later
AP034	0.9.1B2 firmware and later
ZD1000	0.9.3R3 firmware and later
ZD1500	0.9.3R3 firmware and later

Note 1: For Probus Probes not in the list the attenuation factor should be set manually.

Note 2: Probes not in the list have not been tested.

Specifications

Bandwidth	4 GHz
Power Supplies	+12 V ($\pm 2\%$), -12 V ($\pm 2\%$)



TPA10 Specifications

Specifications	
Bandwidth	4 GHz
Power Supplies	+15 V ($\pm 2\%$, 100 mA), -15 V ($\pm 2\%$, 100 mA), +5 V ($\pm 2\%$, 200 mA), -5 V ($\pm 2\%$, 200 mA)
Offset Voltage	-1.2 V ~ +1.2 V to the probe. Multiply it by the attenuation factor of the probe to calculate the system offset range.

